



OPERATING INSTRUCTIONS:

Congratulations on your purchase of The Instant Unlocker system for security control panels. With this system you will be able to instantly reset the installer's code on a panel without having to unhook it. Best of all the current settings will all be maintained saving hours of work since there is no re-installation or reprogramming required.

To use The Instant Unlocker system:

1. Identify a compatible panel you wish to unlock. See conditions below.
2. Insert a Charge Card into the Display POD. The card is "keyed" and can only be inserted one way.
3. Attach the correct Unlock Head for the panel to the Display POD.
4. Attach the Unlock Head to the security system. (Please reference the instructions that came with the Unlock Head to verify correct connection procedure and alignment)
5. When the Unlock Head is properly attached the system will power on. The amount of charges on the card will be displayed on the LCD of the Display POD.
6. Press and hold the Unlock Head to the panel. If the panel is locked the POD's RED LED will light. If the panel is unlocked the GREEN LED will light.
7. Once connected simply press the "START" button to unlock.
8. The RED LED will then flash while the panel is being unlocked. When finished the GREEN LED will light and the Charge Card will be decremented one charge.
9. If the RED LED turns to ORANGE at any point then either the Unlock Head has been attached improperly or the panel is not currently supported by the system. You may also receive an error message (see below)
10. Once successful the new installer's code will be programmed into the system. Please consult the Unlock Head documentation to determine the code for that head.
11. Disconnect the Unlock Head from the panel.

For more information please visit www.instantunlocker.com

DISPLAY MESSAGES:

- no Crd: No Unlock Charge Card inserted in the Display POD
- Err 1: Failed to detect alarm panel
- Err 2: Failed to Unlock alarm panel

IMPORTANT: Please note this product is not to be used on systems currently under contract with an alarm monitoring company. We accept no responsibility for the use or misuse of this product. Using this product may void the warranty on the panel.

WARNING: This product should only be used by professional alarm installers. If used improperly this product could cause damage to the target system or to itself. We are not responsible for any damage caused by the use of the product to either the target system or the device itself. This product is to be used at your own risk.